




**Installing lighting and haning track**



screw hanging track to wall using 5mm countersunk screws




push in lighting track




snap lighting track into place


**connecting halogen lamp to armatures**



recommended lamps: general electric constant color or BLV reflective (coloured).





push in lamp pins, all the way.




(1) screw BOTH screws tightly with M3-driver.

**inserting armatures into lighting track**




push in armature and free-moving contact (against spring pressure)




turn the free-moving contact through 90°

Lighting Instructions


**fastening straight connector**



push in fast lighting track




fasten second lighting track




push in half way second track  
1. screw home tightly all screws


**fastening corner connector**



push in connector




fasten first lighting track




push in second lighting track and fasten track  
1. screw home tightly all screws (M 5)


**fastening power supply connector**



1. connect both cables to transformer, strip 1 cm of other ends and insert into holes  
2. screw home tightly both screws (M 4)



push in lighting track  
1. screw home tightly both screws (M 5)



double input: with 2 x 2 cables  
1. screw home tightly all 6 screws (M 5)